

* Notice:

-

All the follow steps need the device to be online

-

You can use the web ceiba to check the device' online status and device's Serial No.

*

Basic info (IP and Port is the web ceiba used, the default port is 12056)

-

Device Serial No. 0089000EFD

-

Server address <http://IP:12056/>

-

Login username: username

-

Logoin password: password

-

KEY zT908g2j9ng4xe0Nr2n1bvhbSblgS24wXjZV3o9wsVfNq0q3nEdl%2Fw%3D%3D

-

Demo url: <http://IP:12056/h5demo/index.html>

-

API help url <http://IP:12056/help/api/default.html>

*

[LiveView](#):

*

Step1: Get key

-

<http://IP:12056/api/v1/basic/key?username=username&password=password>

-

Return:

```
{"data":{"key":"zT908g2j9ng4xe0Nr2n1bvhbSblgS24wXjZV3o9wsVfNq0q3nEdl%2Fw%3D%3D"},"errorcode":200}
```

*

Step2: Get liveview port:

-

<http://IP:12056/api/v1/basic/live/port?key=zT908g2j9ng4xe0Nr2n1bvhbSblgS24wXjZV3o9wsVfNq0q3nEdl%2Fw%3D%3D>

-

Return: {"data":[{"port":12060}, {"port":12061}, {"port":12062}, {"port":12063}], "errorcode":200}

*

Step3: Get liveview url:

<http://IP:12056/api/v1/basic/live/video?key=zT908g2j9ng4xe0Nr2n1bvhbSblgS24wXjZV3o9wsVfNq0q3nEdl%2Fw%3D%3D>

&terid=0089000EFD&chl=1&audio=1&st=0&port=12060&dt=mdvr

*

Return: {"data":{"url":"<http://IP:12060/live.flv?devid=0089000EFD&chl=1&st=0&isaudio=1&dt=mdvr>"},"errorcode":200}

*

Step4: Open demo and input the url to open the liveview;

*

*

*

Playback:

*

Step 1, Search the record list:

-

<http://IP:12056/api/v1/basic/record/filelist?key=zT908g2j9njDg2AqN6Dqx%2F94dwaNzZOGvJK1x%2FfQUZg%3D%20&terid=00880038EE&starttime=2019-04-18%2000:00:00&endtime=2019-04-19%2023:59:59&chl=1,2,3,4&ft=0&st=1>

-

```
Return:{"data":[{"name":"0-58-0","filetype":1,"chn":2,"starttime":"2019-04-18
00:14:42","endtime":"2019-04-18
00:14:42"}, {"name":"0-58-1","filetype":1,"chn":2,"starttime":"2019-04-18
00:14:42","endtime":"2019-04-18
00:14:48"}, {"name":"0-60-0","filetype":1,"chn":3,"starttime":"2019-04-18
00:14:42","endtime":"2019-04-18
00:14:48"}, {"name":"0-61-0","filetype":1,"chn":4,"starttime":"2019-04-18
00:14:42","endtime":"2019-04-18
00:14:48"}, {"name":"0-63-0","filetype":1,"chn":1,"starttime":"2019-04-18
00:14:42","endtime":"2019-04-18 00:14:48"}], "errorcode":200}
```

*

Step 2, Get the playback url:

-

<http://IP:12056/api/v1/basic/record/video?key=zT908g2j9njDg2AqN6Dqx%2F94dwaNzZOGvJK1x%2FfQUZg%3D&terid=00880038EE&starttime=2019-04-18%2000:14:42&endtime=2019-04-18%2000:14:48&chl=1>

-

```
Return:{"data":{"url":"http://IP:8090/play/00880038EE/1/20190418001442\_20190418001448\_main.m3u8"}, "errorcode":200}
```

*

Step3, playback

-

Fill "http://IP:8090/play/00880038EE/1/20190418001442_20190418001448_main.m3u8" in the demo will be playback

From:

<http://eu.streamax.com:8800/> - Europe_Wiki

Permanent link:

<http://eu.streamax.com:8800/doku.php?id=public:ceiba2:api&rev=1629996339>

Last update: **2021/08/26 18:45**

